

# CM-P3

Fire Alarm Control Panel

ISO9001

Approvals: CE



## ADVANTAGES

- \* Zone range is from 1 to 24 zones
- \* Key-controlled function switches prevent false alarms caused by accidental touch
- \* The fire alarm circuit and indicator circuit are able to detect circuit break and offer protection against short circuit

## ORDER INFORMATION

CM-P3-1L	FACP 01 zone with battery
CM-P3-2L	FACP 02 zone with battery
CM-P3-4L	FACP 04 zone with battery
CM-P3-8L	FACP 08 zone with battery
CM-P3-12L	FACP 12 zone with battery
CM-P3-16L	FACP 16 zone with battery
CM-P3-24L	FACP 24 zone with battery

## SPECIFICATION

MODEL NO.	CM-P3	STAND-BY BATTERY	24V DC Sealed Maintenance -Free Lead-Acid Battery
POWER SUPPLY	240V AC 50/60Hz ± 10%	CHARGING CURRENT	26.4V DC, under 450mA, Trickle Charge
CHARGING VOLTAGE & CURRENT	26V DC Below 450mA Trickle Charging	DETECTORS	No limit of R.O.R. Heat or Fixed Temp. Heat Detector can be installed; Each circuit can connect to a maximum of 20 smoke detectors (standby current for detector: 24V DC 25µA below)
EXTERNAL CIRCUIT	To-and-fro below 50 Ω	REPORT CONTACT	No-voltage Normally-Open contact point Capacity: 250V AC 7A
EOL RESISTOR	10KΩ		
NO. OF INDICATORS	1 times of panel circuits		
NO. OF BELLS	1 times of panel circuits		
CASE MATERIAL	Standard Material of 1.2mm		

## EXTERNAL DIMENSIONS \* Other circuit and dimensions can be order.

MODEL	Wall Mounting Type			
	CIRCUIT NO.	1L/2L/4L/8L	12L/16L	24L
H (mm)		400	495	580
W (mm)		300	300	300
D (mm)		120	120	120

\* Max. 24L